MONOGRAM 30" BUILT-IN DOUBLE OVEN

ZTDXIDPSNSS









THE MONOGRAM STATEMENT COLLECTION

Edge-to-edge handles, polished stainless steel, and hand-finished edges convey a sense of solidity and beauty

LCD CONTROLS

Allow you to adjust oven settings with little effort

WIFI CONNECT

Perfectly in sync with a busy lifestyle, Alexa or Google Home can be used to control an array of oven functions from both inside and outside the home

VOICE CONTROL

Sleek handle-less design now benefits from the convenience of voice control. Once programmed, you can use your voice to open the oven door, preheat the oven and more, all without raising a finger

PRECISION COOKING MODES

Master new recipes and perfectly execute favorite dishes using this ultra-smart system that automatically tracks cooking progress, modifies temperatures and adjusts cook times

SCAN-TO-COOK

Innovative and time saving, scan-to-cook technology ensures that packaged foods are always prepared correctly. A simple scan of the barcode with a smartphone delivers consistently delicious results

TWIN CONVECTION WITH DIRECT AIR

Achieve beautifully cooked and delicious meals every time with this expertly designed, third heating element and fan combination

10.0 CUBIC FOOT OVEN CAPACITY (5.0 EACH OVEN)

Easily accommodates even the largest meals

EXCLUSIVE SELF-CLEAN, (4 FULL-EXTENSION, 2 REGULAR) OVEN RACKS

Glide in and out smoothly on stainless steel ball bearings, and are designed to be left in the oven during the self-clean cycle

TEN-PASS BAKE ELEMENT

Covers more surface area for more even baking results

EIGHT-PASS BROIL ELEMENT

Provides complete coverage and even browning, even for large dishes

SELF-CLEAN WITH STEAM CLEAN OPTION

Gives you flexible options for thorough oven cleaning





SPECIFICATIONS


29 3/4" (75.6 cm)
51 3/16" (130.0 cm)
27 5/16" (70.6 cm)
20 9/16" (52.3 cm)
10.0 cu. ft. (283.2 liters)
25" x 17 3/8" x 20 1/4" (63.5 x 44.1 x 51.4 cm)
30" (76.2 cm)
24" (61.0 cm)
400 lbs. (181 kg)
28 1/2" (72.4 cm) Min 28 5/8" (72.7 cm) Max
49 3/4" (126.3 cm) Min 51 15/16" (131.9 cm) Max
23 1/2" (59.7 cm) Min
240/208 V AC, 60 Hz, 40A
48" (72" available special order: WB18T1O398)
6.8 kW at 208V 9.0 kW at 240V
390 lbs. (178 kg)

^{*} Additional space will be needed for flush installation.

ATTENTION ELECTRICIAN:


A 240/208V, 60Hz, 40 Amp circuit is required. An individual properly grounded branch circuit or circuit breaker is required. Hardware junction box is required for built-in product.

OVERALL DIMENSIONS



FRONT VIEW (SHOWING CUTOUT OVERLAP)





TOP VIEW

Dimensions in parentheses are in centimeters unless otherwise noted. Actual product dimensions may vary due to manufacturing tolerances.



WALL INSTALLATION TOP VIEW 2 1/2" 1 7/16 (6.4) Side cleats depth 30" (76.2) flush inset width with 1/8" (0.3) reveals 24 15/16" (63.3) min cutout depth 23 1/2" (59.7) min cutout depth 1 1/8" (2.8) Top cleat В¬ 5 1/4" \$ ELEC _top cleat σ σ 3/4" (1.9) Side cleats 51 7/16" (130.6) Flush inset height with 28 1/2" (72.4) 49 3/4" (126.3) 1/8" (0.3) reveal at top and bottom σi σ **30"** (76.2) 9/16" (1.4) Bottom cleat (Extends full depth of cabinet) 12' -[C] F (30.5) ended cutout location from floor FLUSH INSET INSTALLATION STANDARD **FLUSH INSET**

INSTALLATION


FRONT VIEW

Allow 1/8" (0.3) clearances from side edges of oven door.

INSTALLATION

Α

INSTALLATION OVER WARMING DRAWER



For more details, refer to the installation instructions for this product on Monogram.com. Dimensions in parentheses are in centimeters unless otherwise noted.

HELPFUL TIPS

- A Based on a user height of 5' 6" to 5' 10"
- B Junction box location (May also be located in adjacent cabinet.)
- Platform must be able to support 400 lbs (181 kg)
- Cabinet surface must be an appearance finished surface for flush installation
- E Cleats may be visible and should be finished to match cabinetry
- E If optional flush install vent trim accessory ZX30VT2 is ordered, please adjust cutout height to 51-1/8" and bottom cleat height to 1/4"
- G Dimension per Warming Drawer requirement